
		COMMANDE ET SIGNALISATION			
CODIFICATION DES INTERRUPTEURS DE TRANCHE DE TYPE BLI					
TYPES	MONTAGE PARTICULIER	CONTACTS		RACCORDEMENT	VERROUILLAGE
Spécification du type	Spécification si produit avec particularité de montage	Spécification du nombre de contacts NO et NF	Spécification du n° de plan spécifique	Spécification des accessoires équipant le produit	Spécification du type de verrouillage
	+ Combinaison - Montage standard	Contact F = à fermeture = NO Contact O = à ouverture = NF	Seulement si montage CNS		- Sans verrouillage
BLIA <i>Interrupteur à commande latérale droite indépendante</i>	FD <i>Fixation Déportée</i>	<i>Exemple :</i>	<i>Exemple :</i>	SF Serre Fils	CAD <i>verrouillage par 1 ou 2 cadenas</i>
BLIB <i>Interrupteur à commande centrale indépendante</i>	CNS <i>Configuration non standard : - soit la disposition ou le repérage des contacts est spécifique - soit le produit est équipé de contacts à recouvrement (dans les 2 cas un plan spécifique est lié à la configuration contacts)</i>	F6-O6	+ENT10897		3242A <i>verrouillage par clé standard n° 3242A (verrouillage dans les 2 positions de manette et clé libre dans les 2 positions)</i>
	CC <i>Commande centrale sur BLI<26 Contacts</i>	6NO+6NF			N° de clé <i>verrouillage par clé non standard n° à définir</i>
	BG <i>Bloc contacts modifiable situé à gauche des contacts</i>				
BLD18A BLD18B B1LI18A B1LI18B BCF1 BCF111 BLD182B BLD183B	BD <i>Bloc contacts modifiable situé à droite des contacts</i>			VE <i>Vis et etriers</i>	CAD3 <i>verrouillage par 3 cadenas</i>
	PAG <i>Poignée à gauche</i>			CLIP 5 <i>Raccordement sur clip de 5 x 0,8 mm</i>	VP+N° de clé <i>verrouillage par clé non standard n° à définir (verrouillage possible dans les 2 positions et clé libre dans 1 seule position)</i>
	MA <i>Montage armoire (poignée extérieure)</i>			ou CLIP 6 <i>Raccordement sur clip de 6,3 x 0,8 mm</i>	CON+N° de clé <i>verrouillage par clé non standard n° à définir Dispositif de condamnation de la tige de commande (65255) Clé libre en position A: l'appareil est condamné (impossibilité de manœuvrer les contacts) Clé prisonnière en position B: l'appareil est manoeuvrable (impossibilité de le condamner)</i>

RED Configuration removed from our offer (consult us)

* This document lists the set of the variants which can be proposed but does not indicate the possible incompatibilities of association (Consult us if necessary)

		CONTROL AND SIGNALING			
CODIFICATION OF BAY AUXILIARY SWITCHES TYPE BLI					
TYPES	SPECIAL ASSEMBLY	CONTACTS		CONNECTIONS	LOCKING
Specification of type	Specification if special assembly of the product	Specification of the number of NO and NC contacts	Specification of the specific scheme number	Specification of the type of connection	Specification of the locking device
	+ Combination - Standard assembly	F Contact = make contact = NO O Contact = break contact = NC	Only for CNS assembly		- Without locking
BLIA <i>Switch with independant right lateral control</i> BLIB <i>Switch with independant central control</i>	FD <i>Displaced mounting</i> CNS <i>Non standard configuration : - Either contact configuration or labelling is specific - Whether the product is equipped with overlapping contacts (In the 2 cases a specific scheme is associated to the contact configuration)</i> CC <i>Central control on BLI<26 Contacts</i> BG <i>Modifiable contacts block located to the left of the contact</i> BD <i>Modifiable contacts block located to the right of the contact</i> PAG <i>Handle at the left of the product</i> MA <i>Monting in a cabinet (handle exterior)</i>	Example : F6-O6 6NO+6NC	Example : +ENT10897	SF <i>Wire clamp</i> VE <i>Screw clamp</i> CLIP 5 <i>Connection on clip 5 x 0,8 mm</i> ou CLIP 6 <i>Connection on clip 6,3 x 0,8 mm</i>	CAD <i>Lockable by 1 or 2 padlocks</i> 3242A <i>Locking by standard key n° 3242A (Possibility to lock in both positions; key free in both positions)</i> N° de clé <i>Locking by other key (Key number to be define)</i> CAD3 <i>Lockable by 3 padlocks</i> VP+N°de clé <i>Locking by other key (Key number to be define) (Possibility to lock both positions; key free only in one position)</i> CON+N°de clé <i>Locking by other key (Key number to be define) Device for locking up command (65255) Key free in position A: the device is lock (Impossible to operate the contacts) Key captive in position B: possibility to operate the device (impossible to lock)</i>
BLD18A BLD18B B1LI18A B1LI18B BCF1 BCF111 BLD182B BLD183B					